



AV8805A

13.2Ch 8K UHD Pre-Amplifier with HEOS® Built-in and Voice Control

The versatile Marantz AV8805A pre-amplifier redefines the audiophile home cinema and music listening experience with 13.2 channel processing capability, 8K pass-through, and support for the latest in surround sound audio formats, such as Dolby Atmos®, DTS:X®, Pro, IMAX Enhanced®, and Auro-3D®. Marantz' proprietary technologies enhance any audio playback for the most demanding of listeners. Stream music throughout your home with HEOS® Built-in for a whole home audio experience from your favourite streaming services. With the new Marantz AV8805A, you get incredible fidelity and unparalleled audio precision.

- 8K/60Hz and 4K/120Hz pass-through support for every entertainment need: With the latest technology in HDMI support, enjoy 8K quality video from your 8K source devices or with 8K upscaling from Full HD or 4K sources.
- Ideal for the most advanced home theatre enthusiast: With 13.2 channel processing and 15.2 channel XLR and RCA outputs, and flexible pre-amplifier stages, enjoy your movies with a system you deserve.
- Featuring the most advanced 3D audio formats: Dolby Atmos®, Dolby Atmos Height Virtualization Technology, DTS:X®, DTS Virtual:X™, DTS:X® Pro, IMAX® Enhanced and Auro-3D® processing are all supported for total flexibility and compatibility.
- Enhanced Audio Return Channel (eARC) HDMI support: Through the main HDMI output, connect your TV via eARC HDMI to allow uncompressed and object-based audio formats like Dolby Atmos® and DTS:X® directly from your smart TV app to your system.
- DTS:X® Pro support: DTS:X® Pro can process up to 13 channels, wowing listeners with the most cutting-edge DTS technology.
- Bringing you leading edge video compatibility: The latest High Dynamic Range format support including HDR10, HDR10+, HLG, Dolby Vision, 4:4:4 colour resolution and BT.2020, as well as Dynamic HDR, to provide miraculous picture quality for brightness, clarity, and contrast.
- Experience the next chapter in movie entertainment: With 8K/60Hz pass-through or upscaling, Dynamic HDR and Quick Media Switching (QMS), enjoy the smoothest, most crystal-clear picture quality available.
- The latest in gaming thrills: With 4K/120Hz pass-through, Variable Refresh Rate (VRR), Auto Low Latency Mode (ALLM) and Quick Frame Transport (QFT), enjoy your gaming experience with amazing imaging with reduced lag and tearing.
- Stream music from your favourite sources: Play songs from Spotify, Amazon Music HD, TIDAL, and more via AirPlay 2, Bluetooth, Wi-Fi, and the HEOS app. (Music streaming services may vary by region)

Modern Musical Luxury































































AV8805A Technical Specifications

Multichannel surround	
DTS HD Master / DTS:X / DTS:X Pro	•/•/•
DTS Neo:X / DTS Neural:X	-/•(11ch)
DTS Virtual:X	•
IMAX Enhanced	•
Dolby TrueHD / Dolby Atmos / Dolby Atmos Height Virtualization	•/•/•
Dolby ProLogic IIz / Dolby Surround	-/•
Auro 3D	•
Multichannel Stereo	•
Max Number of Processing (Preamp) Channels	13.2
Sound Enhancements	
Copper Plated Chassis	•
Power Transformer:	Toroidal
Current Feedback Topology	•
Hyper Dynamic Amplifier Modules (HDAM)	•
Pure Direct	•
Gold Plated RCA Terminals	•
Clock Jitter Reducer	•
Audyssey	MultEQ XT32
Audyssey Dynamic EQ / Dynamic Volume	•
Audyssey LFC	•
Compressed Audio Enhancer: MDAX2	•
Network	
HEOS Multi-room and Streaming	•
Bluetooth Re-transmit for Bluetooth headphones	•
Works with Alexa / Works with Hey Google / Works with Apple Siri	•/•/•
Network Audio Sharing	•
Lossy Formats: MP3 / WMA / AAC	•/•/•
Lossless Formats: FLAC / ALAC / WAV	•)
Lossless formats: FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	•
DSD Audio Streaming	• (2.8/5.6MHz)
Gapless Playback	(FLAC, WAV, ALAC, DSD)
AirPlay Audio Streaming	•
Internet Radio	•
Spotify Connect	•
Streaming Services	Amazon Music HD / TIDAL / Deezer / Tuneln / Napster / Soundcloud / Mood Mix
Compatible with Remote APP for Smart Phones	•
Compatible with Remote APP for Tablets	•
Ethernet Port	•
Wi-Fi	<u>.</u>
Bluetooth	•
HDMI	
HDMI Inputs: Back / Front	7/1
HDCP2.3 support	•
HDMI Outputs: Main / Zone	2/1
Video Conversion Analogue -> HDMI	•
Analogue to HDMI scaling	up to 8K 60/50
HDMI to HDMI scaling	up to 8K 60/50
GUI Overlay on HDMI	•/•
8K/60Hz / 4K/120Hz	
3D / 4K / CEC / ARC	•/•/•
Enhanced ARC	
HDR / HLG / Dolby Vision / HDR10+ / Dynamic HDR	• /•/•/•
ALLM (Auto Low Latency Mode) Pass-through for gaming	•
Variable Refresh Rate / Quick Flame Transport / Quick Media Switching	•/•/•
3D Signal Pass-Through	•
8K signal pass-through / scaling / GUI overlay	•/•/•
4K signal Pass-Through / scaling / GUI Overlay	•/•/•
4K signal Pass-Through / scaling / GUI Overlay HDMI Pass-Through in Standby Mode	•/•/•
4K signal Pass-Through / scaling / GUI Overlay HDMI Pass-Through in Standby Mode Picture Adjust / Noise Reduction	•/•/•
4K signal Pass-Through / scaling / GUI Overlay HDMI Pass-Through in Standby Mode Picture Adjust / Noise Reduction CEC	•/•/• • •/•
4K signal Pass-Through / scaling / GUI Overlay HDMI Pass-Through in Standby Mode Picture Adjust / Noise Reduction CEC DSD Audio Capability	•/•/•
4K signal Pass-Through / scaling / GUI Overlay HDMI Pass-Through in Standby Mode Picture Adjust / Noise Reduction CEC	•/•/• • •/•

HEOS Multi-Room Integrated		•
Multi-Room zones		3
Zone Audio Source: HDMI / Opt, Coax / Network,	USB / Analogue	• (2ch) / • (2ch) / • / •
Zone Audio Output: Speaker / Preout		-/•
Zone HDMI Output from HDMI Source		•
IP Control / RS232 Control / Web Control / App C	Control	•/•/•
IR Flasher In		•
Marantz Remote Bus		•
DC Trigger Output		2
HDMI Diagnostics		•
Others		
Auto Speaker Setup by Microphone		Audyssey MultEQ XT32
FL Display		2 lines + port hole
Graphic User Interface - GUI		Advanced
		• Advanced
ISF Certification		
GUI Languages		9
Setup Assistant		•
Smart Select		•
Firmware Update by Network / USB		•/•
Variable Cross Over		•
Optimized Bass Redirection		•
Bass Sync		•
ECO Mode		•
Auto Power Off		•
Sleep Timer		•
Video Inputs/Outputs		
Composite In / Out		4+1/2
Component In / Out		3/1
HDMI In / Out		7+1/3
Multi-Room Video Out: Video / HDMI		•/•
Audio Inputs/Outputs		
Analogue In / Out		6+1 (1x XLR) / -
Phono (MM) In		•
Digital in: optical / coaxial		2/2
Multi-Room Out: analogue / digital		2/-
Multichannel Pre Out		• (15.2 RCA & 15.2 XLR)
Subwoofer Out		2 (independent)
7.1 multichannel input		•
Other Inputs/Outputs		
Speaker A / B		assignable pre out
Bi-amp drive		assignable pre out
Multi-Room Speaker Terminal		pre out
Front Inputs: Audio / Composite / Digital (Opt) / HDMI / USB		•/•/-/•
USB Audio	DIVII / USB	•
General÷		
Metal Front Panel		
		RC039SR
System Remote Control		
Pre-programmed / Learnable / LCD Display		•/•/•
Power Consumption in W		90
Standby Consumption in W		0.2
CEC Standby Consumption in W		0.5
Network Standby Consumption in W		3.7
Maximum Dimensions		
Antenna: Horizontal: (W x D x H) in mm Antenna: Vertical: (W x D x H) in mm		440 x 410 x 185
w/o Antenna: (W x D x H) in mm		440 x 410 x 248 440 x 389 x 185
Weight in kg		13.7
EAN		

Design and specifications are subject to change by Marantz without notice.

The Bluetooth* word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

www.marantz.com